

# Credentials Compatibility Guide

For Readers & Electronic Locks



	PR10 Proximity - Mini-Mullion	SM10 Smart - Mini-Mullion	MT11   MT15   MTK15   MTMS15   MTMSK15 Multi-Technology - Mullion   Single Gang	MTB11   MTB15   MTKB15 Mobile-Enabled Multi- Technology - Mullion   Single Gang
NFC mobile		•	•	•
Bluetooth® (BLE) Mobile				•
Schlage MIFARE® DESFire® EV1/EV2/EV3		•	•	•
Schlage MIFARE Classic®		•	•	•
Schlage MIFARE Plus®		•	•	•
Multi-technology: Proximity and Schlage MIFARE® DESFire® EV1/EV2/EV3	• <sup>1</sup>	•	•	•
Multi-technology: Proximity and Schlage MIFARE Classic®	• <sup>1</sup>	•	•	•
Multi-technology: Proximity and Schlage MIFARE Plus®	• <sup>1</sup>	•	•	•
MIFARE® DESFire® EV1/EV2/EV3, MIFARE Classic®, and MIFARE Plus® CSN <sup>3</sup>		•	•	•
HID iCLASS®, iCLASS SE®, and Seos® secure application area <sup>2</sup>				
HID Seos® NFC mobile, secure application area <sup>2</sup>				
HID iClass®, iCLASS SE® CSN <sup>3</sup>		•	•	•
LEAF Custom Configuration (Cc) credentials		•	•	•
Proximity	•	•	•	•
ISONAS™ Proximity	•		•	•
HID® Proximity <sup>4</sup>	•		•	•
GE/CASI ProxLite®	•		•	•
AWID® Proximity	•		•	•
LenelProx®	•		•	•
Personal Identification Number (PIN)			•	•
Magnetic stripe			•	
PIV and PIV-I		•	•	•

1. Proximity only.

2. Requires Si or SiK option. Si/SiK option does not support proximity credentials.

3. Card serial number only.

4. Proximity bit lengths greater than 37 not supported.

5. Excludes AD-250.

6. No Tour functionality requires minimum 1K byte/8k bit Schlage smart credential and MT20W enrollment reader.

7. Not compatible with Schlage MIFARE DESFire EV2 credentials.

8. Requires FMK reader.

Note: If your credential is not listed, please contact Allegion credential engineering services at [ElectronicInsideSales@allegion.com](mailto:ElectronicInsideSales@allegion.com).



	RC11   RC15   RCK15 Multi-Technology Reader-Controller – Mullion   Single Gang	MT20 (USB) or MT20W (Wi-Fi) Smart Enrollment	CO-200/220 Electronic Locks	AD Series Electronic Locks <sup>5</sup>	LE & NDE Mobile Enabled Wireless Locks <sup>6</sup>	Schlage Control <sup>®</sup> Mobile Enabled Smart Locks <sup>6</sup>
NFC mobile	•			•	•	
Bluetooth <sup>®</sup> (BLE) Mobile	•	•			•	•
Schlage MIFARE <sup>®</sup> DESFire <sup>®</sup> EV1/EV2/EV3	•	•		•	•	• <sup>6</sup>
Schlage MIFARE Classic <sup>®</sup>	•	•		•	•	•
Schlage MIFARE Plus <sup>®</sup>	•	•		•	•	•
Multi-technology: Proximity and Schlage MIFARE <sup>®</sup> DESFire <sup>®</sup> EV1/EV2/EV3	•	•	• <sup>1</sup>	•	•	• <sup>7</sup>
Multi-technology: Proximity and Schlage MIFARE Classic <sup>®</sup>	•	•	• <sup>1</sup>	•	•	•
Multi-technology: Proximity and Schlage MIFARE Plus <sup>®</sup>	•	•	• <sup>1</sup>	•	•	•
MIFARE <sup>®</sup> DESFire <sup>®</sup> EV1/EV2/EV3, MIFARE Classic <sup>®</sup> , and MIFARE Plus <sup>®</sup> CSN <sup>3</sup>	•			•	•	
HID iCLASS <sup>®</sup> , iCLASS SE <sup>®</sup> , and Seos <sup>®</sup> secure application area <sup>2</sup>				•	•	
HID Seos <sup>®</sup> NFC mobile, secure application area <sup>2</sup>				•	•	
HID iClass <sup>®</sup> , iCLASS SE <sup>®</sup> CSN <sup>3</sup>	•			•	•	
LEAF Custom Configuration (Cc) credentials	•	•		•	•	•
Proximity	•		•	•	•	
ISONAS <sup>™</sup> Proximity	•		•	•	•	
HID <sup>®</sup> Proximity <sup>4</sup>	•		•	•	•	
GE/CASI ProxLite <sup>®</sup>	•		•	•	•	
AWID <sup>®</sup> Proximity	•		•	•	•	
LenelProx <sup>®</sup>	•			•	•	
Personal Identification Number (PIN)	•		•	•		
Magnetic stripe			•	•		
PIV and PIV-I	•	•		• <sup>8</sup>		

1. Proximity only.

2. Requires Si or SiK option. Si/SiK option does not support proximity credentials.

3. Card serial number only.

4. Proximity bit lengths greater than 37 not supported.

5. Excludes AD-250.

6. No Tour functionality requires minimum 1K byte/8k bit Schlage smart credential and MT20W enrollment reader.

7. Not compatible with Schlage MIFARE DESFire EV2 credentials.

8. Requires FMK reader.

Note: If your credential is not listed, please contact Allegion credential engineering services at [ElectronicInsideSales@allegion.com](mailto:ElectronicInsideSales@allegion.com).

[Learn more about Schlage Credentials and Services](#)

[Learn more about Schlage readers](#)

[Learn more about Schlage electronic locks](#)