



NOTES:
 1) ALL LOW VOLTAGE WIRING TO BE STANDARD, MULTI-CONDUCTOR CORD CODED WITHOUT SPLICES.
 2) WIRING TO CONFORM TO APPLICABLE NATIONAL, STATE AND LOCAL ELECTRICAL CODES.
 3) REFER TO SPECIFIC PRODUCT INSTALLATION INSTRUCTIONS FOR SPECIFIC WIRING REQUIREMENTS.
 4) THIS DRAWING IS FOR GRAPHICAL REPRESENTATION OF PRODUCTS DETAILED IN THE HARDWARE SET ONLY.
 5) * CONDUCTOR COUNT TO BE DETERMINED BY ACCESS CONTROL PANEL PROVIDER.

HARDWARE USED:

- 1 BADGEPASS BAC042500
- 3 UL294 12/24VDC POWER SUPPLIES
- 1 PIM400-485
- 2 AD-400
- 1 AD-300
- 1 ELECTRIC HINGE

DEPARTING: BADGEPASS BAC042500 WILL SUPPORT UP TO SIXTEEN PIM400-485 ACROSS TWO RS485 DATA LINES WITH NO MORE THAN EIGHT PIM400-485 AND AD300 COMBINED PER RS485 DATA LINE. EACH PIM400-485 IS CAPABLE OF CONTROLLING UP TO SIXTEEN AD400 LOCKS. BAC042500 CAN HANDLE UP TO SIXTY-FOUR AD400/AD300 LOCKS TOTAL COMBINED.
 UL294 POWER SUPPLIES USED SHOULD NOT BOND EARTH GROUND TO SIGNAL GROUND.
 IF PLENUM RATED CABLE IS REQUIRED USE BELDEN 82942 OR EQUIVALENT.
 WIRING SHOWN REFLECTS WIRING FROM BAC042500 TO PIM400-485 AND AD300 LOCK ONLY. ADDITIONAL WIRING WILL BE REQUIRED AND IS NOT SHOWN HERE.
 SHIELD ON COMMUNICATION WIRES: BELDEN 3106A SHOULD CONNECT TO EARTH GROUND AT ONE LOCATION ONLY. BAC042500.
 NOTE: CONFIGURATION HAS NOT BEEN TESTED BY ALLEGION BUT HAS BEEN REVIEWED AND APPROVED BY

TITLE: BADGEPASS BAC042500 WITH PIM400-485 AND AD400/AD300

110384

ALLEGION™

DATE DRAWN: 03-28-12

REVISION DATE: 05-13-14

APPROVED BY: LINDSAY MARTIN-NEZ

DATE: 03-28-12

REVISED BY: BRENDA DOVE

REV: A