



- NOTES:
- 1) ALL LOW VOLTAGE WIRING TO BE STANDARD, MULTI-CONDUCTOR COLOR CODED WITHOUT SPLICES.
 - 2) WIRING TO CONFORM TO APPLICABLE NATIONAL, STATE AND LOCAL ELECTRICAL CODES.
 - 3) REFER TO SPECIFIC PRODUCT INSTALLATION INSTRUCTIONS FOR SPECIFIC WIRING REQUIREMENTS.
 - 4) THIS DRAWING IS FOR GRAPHICAL REPRESENTATION OF PRODUCTS DETAILED IN THE HARDWARE SET ONLY.
 - 5) * CONDUCTOR COUNT TO BE DETERMINED BY ACCESS CONTROL PANEL PROVIDER.

OPERATION:

MERCURY EP-2500 WILL SUPPORT UP TO SIXTEEN PIM400-485 ACROSS TWO RS485 DATA LINES WITH NO MORE THAN EIGHT PIM400-485 PER RS485 DATA LINE. EACH PIM400-485 IS CAPABLE OF CONTROLLING UP TO SIXTEEN AD400 LOCKS. EP-2500 CAN HANDLE UP TO SIXTY-FOUR AD400 LOCKS TOTAL.

UL294 POWER SUPPLIES USED SHOULD NOT BOND EARTH GROUND TO SIGNAL GROUND. GWE MAY BE P.E. NOT SHOWN ON THIS DIAGRAM. IF PLENUM RATED CABLE IS REQUIRED USE BELDEN 82842 OR EQUIVALENT.

WIRING SHOWN REFLECTS WIRING FROM EP-2500 TO PIM400-485 ONLY. ADDITIONAL WIRING WILL BE REQUIRED AND IS NOT SHOWN HERE.

SHIELD ON COMMUNICATION WIRES: BELDEN 3106A, SHOULD CONNECT TO EARTH GROUND AT ONE LOCATION ONLY. EP-2500. NOTE: CONFIGURATION HAS NOT BEEN TESTED BY ALLEGION BUT HAS BEEN REVIEWED AND APPROVED BY

DATE DRAWN:

05-01-18

REVISION DATE:

05-04-18

APPROVED BY:

JASON GARCIA

TITLE:

PANASONIC - MERCURY EP-2500 WITH PIM400-485 AND AD400



DWG NO: 112302

DRAWING CHECKED BY: BRENDA DOVE 05/01/18

REV: A